

# Dusk Pendant & Small Dusk Pendant - DK & SDK



**studio haran**

Please read the instructions carefully before using this product.  
Your light fitting should be installed by a qualified electrician.

**Caution: Please ensure electricity supply is switched off before installing the light.**

## Installation instructions:

1. Switch off electricity supply. Before making any electrical connections ensure the metal lamp holder (A) is connected to the cable and parts are fed on in the following order:
  - i. E27 lampholder (A)
  - ii. ceiling rose (C)
2. Slide the ceiling rose along the cable until you have a suitable drop length for your space. Tighten the cord grip (D) fully from the inside of the ceiling rose to fix the cable at this length.
3. You can now cut off the excess cord ensuring you leave enough cord left to make electrical connections.
4. Attach the metal bracket (E) to the ceiling using the 2x 4x40mm screws and rawlplugs supplied.
5. Using a 3 pole terminal block (minimum rating 4A, 250V, not included) make the appropriate electrical connections. The brown wire is live, the blue is neutral and the yellow and green is earth. A screwed or screwless 3 terminal block with a minimum rating of 4A and 250V, should be used. The terminal block used must conform with IEC 60998-2-1 or IEC 60998-2-2. The ends of the lighting cable should be prepared by removing the fabric braided outer and white insulating layer by 40mm, each of the three inner cores should have their coloured insulating layer stripped back by 10mm, revealing the stranded copper core. The terminal block can remain inside the ceiling rose without being fixed.
6. The metal lampholder (A) and metal bracket (E) must be earthed.
7. Once all electrical connections are complete the connections and wires can be pushed into the ceiling cavity or remain within the ceiling rose (C).
8. The ceiling rose (C) can now be screwed into the metal bracket with the 2 x m3 screws provided.
9. Remove the collar and bottom shade ring, feed the ceramic shade over the lampholder.
10. Return the collar and shade ring to the lampholder and screw the shade ring, the ceramic shade and collar snugly together. Avoid over-tightening to prevent damage to the shade.
11. With everything switched off you can now screw in your E27 light bulb (Max 25W not included).

## Maintenance and Care

**Before conducting any maintenance, ensure light is switched off.**

- Before replacing a defective bulb turn off the light at the switch and let the bulb cool down for at least 10 minutes
- Only change the bulb if it has completely cooled down. Use a clean cloth to help replace the bulb and try to avoid touching the glass with bare hands.
- If necessary the pendant light can be cleaned using a slightly damp cloth. Do not immerse in water.
- The pendant light is designed for indoor use only.
- If the external flexible cable or cable is damaged it shall be replaced by a qualified electrician in order to avoid a hazard.
- Young children should be supervised at all times to ensure they do not play with appliances.
- Position the cable so it will not become a hazard.

## Technical Specifications

- Voltage: 220-240V 50Hz
- Rated Power: 25W Max
- Bulb Type: E27 Max 25W bulb (not included)
- Ingress Protection: IP20
- Cord length : Approx 1.5m
- Dimmable when used with a suitable bulb and switch
- Brass Ceiling Rose, Ceramic Lamphshade, Brass E27 Lampholder



## Dusk Pendant Light Assembly

