

XL Dawn Pendant - XDNP-O(na)



studio haran

Please read the instructions carefully before using this product.
Your light fitting should be installed by a qualified electrician.

Caution: Please ensure electricity supply is switched off before installing the light.

Installation instructions:

1. Switch off electricity supply. Before making any electrical connections ensure the metal lamp holder (A) is connected to the cable and parts are fed on in the following order:
 - i. E26 lampholder (A)
 - ii. oak cap & (B) suspension wire (L)
 - iii. ceiling rose (C)
2. Slide the ceiling rose along the cable until you have a suitable drop length for your space. Tighten the cord grip (D) fully from the inside of the ceiling rose to fix the cable at this length.
3. You can now cut off the excess cord ensuring you leave enough cord left to make electrical connections.
4. Attach the metal bracket (E) to the ceiling using the 8-32 screws supplied.
5. Using a terminal block (not included) make the appropriate electrical connections. The white wire is neutral, the black is live and the green is earth. The ends of the lighting cable should be prepared by removing the fabric braided outer and white insulating layer by 40mm, each of the inner cores should have their coloured insulating layer stripped back by 10mm, revealing the stranded copper core. The terminal block can remain inside the ceiling rose without being fixed.
6. The E26 lamp holder (A) and metal bracket (E) must be earthed.
7. Once all electrical connections are complete the connections and wires can be pushed into the junction box or remain within the ceiling rose.
8. You may now adjust the suspension wire (L), please read the following instructions carefully.
9. Attached to the ceiling rose is a metal clutch. Partially unscrew the collar to loosen.
10. Push the wire through the clutch toward the ceiling rose to shorten.
11. To lengthen, push the loosened collar toward the ceiling rose. This will release the sprung clutch and allow you to lengthen the wire (L).
12. Ensure that the suspension wire (L) is slightly shorter than the lamp's cable in order to **take the entirety of the lamp's weight**. There should be no weight suspended from the lamp cable.
13. When you have the suspension wire set to the correct length, fully tighten the collar on the suspension wire clutch (M). Please note, the suspension wire must be earthed using the terminal inside the ceiling rose.
14. The ceiling rose (C) can now be screwed into the bracket (E) with the 2 x m4 screws provided.
15. Slide the ceramic shade (F) over the lamp holder followed by the oak collar (G)
16. Ensure the lamp holder (A) is sitting inside the oak collar (G) and the ceramic shade is sitting on top of the oak collar (G) in a level position.
17. The metal shade ring (H) should be screwed onto the lamp holder, just enough for it to be held on securely but not all the way up the thread.
18. The oak cap (B) can now rest on top of the ceramic shade (F).
19. With everything switched off you can now screw in your E26 light bulb (25W max, not included).

Maintenance and Care

Before conducting any maintenance, ensure light is switched off.

- Before replacing a defective bulb turn off the light at the switch and let the bulb cool down for at least 10 minutes
- Only change the bulb if it has completely cooled down. Use a clean cloth to help replace the bulb and try to avoid touching the glass with bare hands.
- If necessary the pendant light can be cleaned using a slightly damp cloth. Do not immerse in water.
- The pendant light is designed for indoor use only.
- If the external flexible cable or cable is damaged it shall be replaced by a qualified electrician in order to avoid a hazard.
- Young children should be supervised at all times to ensure they do not play with appliances.
- Position the cable so it will not become a hazard.

Technical Specifications

- Voltage: 110-220V 60Hz
- Rated Power: 25W Max
- Bulb Type: E26 Max 25W bulb (not included)
- Ingress Protection: IP20
- Cord length : Approx 1.5m
- Dimmable when used with a suitable bulb and switch
- Wooden Collar and Ceiling Rose, Ceramic Lamphshade, Brass E26 Lampholder



XL Dawn Pendant Assembly

